### 460BCTCP-N2E

### **Ethernet TCP/IP to BACnet/IP**

## **FEATURES**

- Fully configurable BACnet/IP client
- BACnet/IP supports device, binary I/O/V, analog I/O/V, multistate I/O/V, and character string value object types
- Support up to 10 TCP/IP devices
- Parse & concatenate ASCII/HEX data in up to 50 segments by delimiter or offset
- Effortless Browser
   Based Configuration,
   no programming
   software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- 5-Year Hardware Warranty

# Get Ethernet TCP/IP Data into Your BACnet/IP Server Devices

The 460BCTCP moves data between up to 32 BACnet/IP server devices and up to 10 Ethernet TCP/IP connections.

It's a great tool to implement BACnet/IP devices into your PC or embedded applications that support Ethernet sockets.

#### How Do I Use the 460BCTCP-N2E in My Application?

BACnet analog, binary and CSV data segments can be converted to ASCII and delivered to your ASCII controller. If you need to command the BACnet/IP servers an incoming ASCII string can be parsed and directed to user-defined data location. Need to scale your data or manipulate it with other math functions? The 460BCTCP allows you to add scaling to any data, apply simple math operations, add alarming, and control the request speeds of your server devices.

#### Why Use Real Time Automation as a Gateway Supplier?

While there are certainly other companies offering protocol gateways, there is no one who provides the level of support and service that you receive from RTA.

When you call, a live person answers the phone. When you talk with sales, you will get honest answers and recommendations. When you get support, it is from an engineer who had a hand in the product's development, and support doesn't require a ticket or 24-hour wait.



A Solution, A Philosophy, the RTA Way. We understand the long hours spent on a factory floor and the pressure to keep a line running and product flowing. That's how Real Time Automation came to be. You want easy-to-use solutions where the hardest part is to open the box. You need customer support second to none. If you get all that and a fun customer experience all the better. Thirty years later, our mission remains the same: To move your data where you need it, when you need it, and how you need it.

## **Specification**

BACNET IP CLIENT FEATURES	
Operation Mode	BACnet/IP Client
Supported Object Types	Device, BI/BO/BV, AI/AO/AV, MI/MO/MV, Character String Value
Supported Service Codes	Read Property-A, Read Property Multiple-A, Write Property-A, Write Property Multiple-A, Device Dynamic Binding-A
Maximum Connections	32
Number Read/Write Scan Lines per Device	200 Total - 100 reads & 100 writes
Scan Line Support	Up to 128 Objects
ETHERNET TCP/IP FEATURES	
Operation Mode	Client or Server
Maximum Number of Devices Supported	10
Maximum Number of Characters Transferred	1024
Delimiter Processing	Incoming delimiters can be automatically removed; Outgoing delimiters automatically added if configured
Parsing	Parse String of ASCII Data in up to 50 Segments by Delimiter or Offset
Concatenation	Concatenate up to 50 segments/strings of ASCII data with optional delimiter
INCLUDED WITH GATEWAY	
3' power cable with flying leads	5-year hardware warranty
IPSetup software – automatically locates RTA gateway on the network	Unlimited firmware feature upgrades for life
CAT5 crossover cable for direct connection to PC during programming	Complete, unlimited access to our industry leading support staff
Manual	

Status and Counters  Status and Counters  Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a	<b>ELECTRICAL / ENVIRONMENTA</b>	AL	
Operating Temperature  -40 C to 85 C  Certification  ROHS-Compliant, UL, CUL, CE Approvals, Class 1 Div 2  ENCLOSURE / HARDWARE Size  5.40" x 3.83" x 1.19" Weight  7.6 oz Enclosure Type Anodized Aluminum Mounting Din rail or panel mount LEDs Power LED & 2 general purpose LEDs on side GATEWAY FEATURES & FUNCTIONS  Set <, <, >, >=, ==, !=, and change-of-state rules on any data moving through the gateway. If alarm rule is triggered an email notification can be sent.  Gateway Security  You can configure up to 9 different users access to diagnostic and configuration screens.  Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.  Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.  NOT EXACTLY WHAT YOU WERE LOOKING FOR Real Time Automation offers a full line of gateway profice us a call at 1-800-249-1612. Or, check out a list www.rtautomation.com/products, We also offe customizations for unique applications.	DC Input Voltage	12-24 VDC	
RoHS-Compliant, UL, CUL, CE Approvals, Class I Div 2  ENCLOSURE / HARDWARE Size  5.40" x 3.83" x 1.19"  Weight  7.6 oz  Anodized Aluminum  Mounting  Din rail or panel mount  LEDs  Power LED & 2 general purpose LEDs on side  GATEWAY FEATURES & FUNCTIONS  Set <, <=, >, ==, !=, and change-of-state rules on any data moving through the gateway. If alarm rule is triggered an email notification can be sent.  You can configure up to 9 different users access to diagnostic and configuration screens.  Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.  Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.  NOT EXACTLY WHAT YOU WERE LOOKING FOR Real Time Automation offers a full line of gateway products. We also offer customizations for unique applications.  Allows users to see and log start up sequences,  Allows users to see and log start up sequences,	Maximum Baud Rate	115K baud	□ (e   □ m
ENCLOSURE / HARDWARE  Size  5.40" x 3.83" x 1.19"  Weight  7.6 oz  Enclosure Type  Anodized Aluminum  Mounting  Din rail or panel mount  LEDs  Power LED & 2 general purpose LEDs on side  GATEWAY FEATURES & FUNCTIONS  Set <, <, >, >, =, =,!=, and change-of-state rules on any data moving through the gateway. If alarm rule is triggered an email notification can be sent.  You can configure up to 9 different users access to diagnostic and configuration screens.  Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.  Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.  Plagmostic Logging Page  Allows users to see and log start up sequences,  Allows users to see and log start up sequences,	Operating Temperature	-40 C to 85 C	
Size  5.40" x 3.83" x 1.19"  Weight  7.6 oz  Enclosure Type  Anodized Aluminum  Mounting  LEDs  Power LED & 2 general purpose LEDs on side  GATEWAY FEATURES & FUNCTIONS  Alarming  Set <, <=, >>=, ==,!=, and change-of-state rules on any data moving through the gateway. If alarm rule is triggered an email notification can be sent.  You can configure up to 9 different users access to diagnostic and configuration screens.  Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.  Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.  Piagnostic Lorging Page  Allows users to see and log start up sequences,  Allows users to see and log start up sequences,	Certification		3.83
Weight 7.6 oz Enclosure Type Anodized Aluminum Mounting Din rail or panel mount LEDs Power LED & 2 general purpose LEDs on side GATEWAY FEATURES & FUNCTIONS  Alarming Set <, <=, >, >=, ==,!=, and change-of-state rules on any data moving through the gateway. If alarm rule is triggered an email notification can be sent.  You can configure up to 9 different users access to diagnostic and configuration screens.  Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.  Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.  NOT EXACTLY WHAT YOU WERE LOOKING FOR Real Time Automation offers a full line of gateway profice us a call at 1-800-249-1612. Or, check out a list www.rtautomation.com/products. We also offer customizations for unique applications.  Allows users to see and log start up sequences,	ENCLOSURE / HARDWARE		0 0 1 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0
Enclosure Type Anodized Aluminum  Mounting Din rail or panel mount  LEDs Power LED & 2 general purpose LEDs on side  GATEWAY FEATURES & FUNCTIONS  Alarming Set <, <=, >, >=, ==, !=, and change-of-state rules on any data moving through the gateway. If alarm rule is triggered an email notification can be sent.  You can configure up to 9 different users access to diagnostic and configuration screens.  Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.  Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.  Allows users to see and log start up sequences,  Allows users to see and log start up sequences,	Size	5.40" x 3.83" x 1.19"	
is triggered an email notification can be sent.  You can configure up to 9 different users access to diagnostic and configuration screens.  Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.  Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.  NOT EXACTLY WHAT YOU WERE LOOKING FOR Real Time Automation offers a full line of gateway profice us a call at 1-800-249-1612. Or, check out a list www.rtautomation.com/products. We also offer customizations for unique applications.  Allows users to see and log start up sequences,	Weight	7.6 oz	
is triggered an email notification can be sent.  You can configure up to 9 different users access to diagnostic and configuration screens.  Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.  Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.  NOT EXACTLY WHAT YOU WERE LOOKING FOR Real Time Automation offers a full line of gateway profice us a call at 1-800-249-1612. Or, check out a list www.rtautomation.com/products. We also offer customizations for unique applications.  Allows users to see and log start up sequences,	Enclosure Type	Anodized Aluminum	
is triggered an email notification can be sent.  You can configure up to 9 different users access to diagnostic and configuration screens.  Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.  Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.  NOT EXACTLY WHAT YOU WERE LOOKING FOR Real Time Automation offers a full line of gateway profice us a call at 1-800-249-1612. Or, check out a list www.rtautomation.com/products. We also offer customizations for unique applications.  Allows users to see and log start up sequences,	Mounting	Din rail or panel mount	
is triggered an email notification can be sent.  You can configure up to 9 different users access to diagnostic and configuration screens.  Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.  Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.  NOT EXACTLY WHAT YOU WERE LOOKING FOR Real Time Automation offers a full line of gateway profice us a call at 1-800-249-1612. Or, check out a list www.rtautomation.com/products. We also offer customizations for unique applications.  Allows users to see and log start up sequences,	LEDs	Power LED & 2 general purpose LEDs on side	
is triggered an email notification can be sent.  You can configure up to 9 different users access to diagnostic and configuration screens.  Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.  Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.  NOT EXACTLY WHAT YOU WERE LOOKING FOR Real Time Automation offers a full line of gateway profice us a call at 1-800-249-1612. Or, check out a list www.rtautomation.com/products. We also offer customizations for unique applications.  Allows users to see and log start up sequences,			
diagnostic and configuration screens.  Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.  Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.  NOT EXACTLY WHAT YOU WERE LOOKING FO Real Time Automation offers a full line of gateway profice us a call at 1-800-249-1612. Or, check out a list www.rtautomation.com/products. We also offe customizations for unique applications.  Allows users to see and log start up sequences,	Alarming	any data moving through the gateway. If alarm rule	
Translation Table  translation. Scaling and other data format changes can occur in the gateway.  Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.  NOT EXACTLY WHAT YOU WERE LOOKING FO Real Time Automation offers a full line of gateway profive us a call at 1-800-249-1612. Or, check out a list www.rtautomation.com/products. We also offe customizations for unique applications.  Allows users to see and log start up sequences,	Gateway Security	9 ,	
Status and Counters  Status and Counters  Status and Counters  Real Time Automation offers a full line of gateway program also be delivered to a connected device.  Real Time Automation offers a full line of gateway program as a call at 1-800-249-1612. Or, check out a list www.rtautomation.com/products. We also offer customizations for unique applications.	Translation Table	translation. Scaling and other data format changes	
Diagnostic Logging Dago	Status and Counters	messages are accessible within the gateway's diagnostics page. They can also be delivered to a	NOT EXACTLY WHAT YOU WERE LOOKING FOR?  Real Time Automation offers a full line of gateway products.  Give us a call at 1-800-249-1612. Or, check out a listing at   www.rtautomation.com/products. We also offer  customizations for unique applications.
	Diagnostic Logging Page		

CATALOG #	DESCRIPTION
460BCTCP-N2E	Connects up to 32 BACnet/IP servers with up to 10 Ethernet TCP/IP devices









