

CONTACT US! 1-800-249-1612 rtautomation.com

460ECUS-NNA1

EtherNet/IP to OPC UA

FEATURES

- Fully configurable EtherNet/IP scanner
- Map data from up to 32 EtherNet/IP adapters
- Fully configurable OPC UA server
- Up to 10 read and write groups with up to 200 nodes per group
- Effortless Browser Based Configuration, no programming software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- 5-Year Hardware Warranty

Connect EtherNet/IP Adapter Devices Directly to OPC UA

The 460ECUS moves data between EtherNet/IP adapters to OPC UA Best of all, the product comes with 5-year warranty.


How Do I Use the 460ECUS-NNA1 in My Application?

Bytes of data in your Ethernet/IP adapters are mapped to OPC nodes. The data moves bidirectionally. It really is that simple.

Why Use Real Time Automation as a Gateway Supplier?

While there are certainly other companies offering protocol gateways, there is no one who provides the level of support and service that you receive from RTA.

When you call, a live person answers the phone. When you talk with sales, you will get honest answers and recommendations. When you get support, it is from an engineer who had a hand in the product's development, and support doesn't require a ticket or 24-hour wait.







#C+=1

Client

A Solution, A Philosophy, the RTA Way. We understand the long hours spent on a factory floor and the pressure to keep a line running and product flowing. That's how Real Time Automation came to be. You want easy-to-use solutions where the hardest part is to open the box. You need customer support second to none. If you get all that and a fun customer experience all the better. Thirty years later, our mission remains the same: To move your data where you need it, when you need it, and how you need it.

Specification

ETHERNET/IP SCANNER FEATURES			
Operation Mode	Class 1 I/O Scanner		
Message Support	Implicit Class 1 Cyclic I/O, Explicit not supported		
Data Types	BIT8,16 & 32; INT8, 16, 32 & 64; UINT8,16, 32 & 64; Float & Double		
Maximum EtherNet/IP Adapter Devices	32		
Max Data Per Adapter Connection	Up to 496 bytes in each direction		
Maximum IO Scan Rate	50 msec		
OPCUA SERVER FEATURES			
Operation Mode	OPC UA Server		
Simultaneous Connections Supported	3		
Max number of Input Nodes per Node Type	200		
Max number of Output Nodes per Node Type	200		
Array Support	Boolean,64 Bit Integer, 64 Bit Unsigned Int and 64 bit Float		
Profiles Supported	UA 1.03 Micro Embedded Server and Data Access		
INCLUDED WITH GATEWAY			
3' power cable with flying leads	5-year hardware warranty		
IPSetup software – automatically locates RTA gateway on the network	Unlimited firmware feature upgrades for life		
CAT5 crossover cable for direct connection to PC during programming	Complete, unlimited access to our industry leading support staff		
Manual			

ELECTRICAL / ENVIRONMENTA	1	
DC Input Voltage	12-24 VDC	
Maximum Baud Rate	115K baud	DIN Rail Mount
Operating Temperature	-40 C to 85 C	
Certification	RoHS-Compliant, UL, CUL, CE Approvals	3.88
ENCLOSURE / HARDWARE	Rons-compliant, OE, COE, CE Approvais	
Size	3.88" x 2.57" x 1.06"	
Weight	5.5 oz	
Enclosure Type	Anodized Aluminum	2.57
/1	Din rail or panel mount	
Mounting LEDs	Power LED & 2 general purpose LEDs on side	Note: All dimensions
	• • • •	are in Inches
GATEWAY FEATURES & FUNCTIONS		
Alarming	Set <, <=, >, >=, ==, !=, and change-of-state rules on	
	any data moving through the gateway. If alarm rule	66666 66
	is triggered an email notification can be sent.	
Gateway Security	You can configure up to 9 different users access to	
	diagnostic and configuration screens.	
Translation Table	Allows for data manipulation during protocol	
	translation. Scaling and other data format changes	
	can occur in the gateway.	
		NOT EXACTLY WHAT YOU WERE LOOKING FOR?
Status and Counters	Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.	Real Time Automation offers a full line of gateway products.
		Give us a call at 1-800-249-1612. Or, check out a listing at
		www.rtautomation.com/products. We also offer
		customizations for unique applications.
	Allows users to see and log start up sequences,	
Diagnostic Logging Page	protocol specific messages & error messages.	
	protocor specific messages & error messages.	















solutions@rtautomation.com