

CONTACT US! 1-800-249-1612 rtautomation.com

460ESAWS-N2E

EtherNet/IP Scanner to Amazon Web Services (AWS)

FEATURES

- Fully configurable EtherNet/IP adapter
- Up to 480 bytes in each direction per adapter connection
- AWS Certified Product
- Allows factory floor based devices to move its data to IT
- Effortless Browser Based Configuration, no programming software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- 5-Year Hardware Warranty

Connect an EtherNet/IP PLC to AWS IoT Core

The 460ESAWS moves data between an EtherNet/IP scanner and the AWS platform. Allowing you to easily log data and leverage in populating dashboards. Best of all, the product comes with 5-year warranty.

How Do I Use the 460ESAWS-N2E in My Application?

Map EtherNet/IP implicit IO data to topics in your AWS platform. SSL transport layer security protects the data moving from your operations network to the cloud.

Why Use Real Time Automation as a Gateway Supplier?

While there are certainly other companies offering protocol gateways, there is no one who provides the level of support and service that you receive from RTA.

When you call, a live person answers the phone. When you talk with sales, you will get honest answers and recommendations. When you get support, it is from an engineer who had a hand in the product's development, and support doesn't require a ticket or 24-hour wait.



A Solution, A Philosophy, the RTA Way. We understand the long hours spent on a factory floor and the pressure to keep a line running and product flowing. That's how Real Time Automation came to be. You want easy-to-use solutions where the hardest part is to open the box. You need customer support second to none. If you get all that and a fun customer experience all the better. Thirty years later, our mission remains the same: To move your data where you need it, when you need it, and how you need it.

Specification

| ETHERNET/IP ADAPTER FEATURES | |
|---|--|
| Operation Mode | Class 1 I/O Adapter |
| Message Support | Implicit Class 1 Cyclic I/O, Explicit Class 3 and UCMM Supported |
| Data Types | BIT8,16 & 32; INT8, 16, 32 & 64; UINT8,16, 32 & 64; Float & Double |
| Maximum EtherNet/IP Scanner Devices | Up to 10 can listen, only 8 can write I/O |
| Maximum Data Supported | Up to 480 bytes in each direction per adapter connection |
| Maximum IO Scan Rate | 20 msec |
| MQTT CLIENT FEATURES | |
| Operation Mode | Amazon Web Services (AWS) |
| Max Broker Connections | 1 AWS |
| Max Data Points Per Connection | 250 Read Topics, 250 Write Topics |
| Security | SSL certificate based cloud access |
| Supported Data Formats | JSON |
| Data Payload | Topic Name and Value |
| INCLUDED WITH GATEWAY | |
| 3' power cable with flying leads | 5-year hardware warranty |
| IPSetup software – automatically locates RTA gateway on the network | Unlimited firmware feature upgrades for life |
| CAT5 crossover cable for direct connection to PC during programming | Complete, unlimited access to our industry leading support staff |
| Manual | |

ELECTRICAL / ENVIRONMENTAL DC Input Voltage 12-24 VDC Maximum Baud Rate 115K baud -40 C to 85 C **Operating Temperature** RoHS-Compliant, UL, CUL, CE Approvals, Class 3.83 Certification 1.19 I Div 2 **ENCLOSURE / HARDWARE** 5.40" x 3.83" x 1.19" Size o Weight 7.6 07 Enclosure Type Anodized Aluminum 5.40 Mounting Din rail or panel mount Power LED & 2 general purpose LEDs on side LEDs **GATEWAY FEATURES & FUNCTIONS** 8 Set <, <=, >, >=, ==, !=, and change-of-state rules on any data moving through the gateway. If alarm rule Alarming is triggered an email notification can be sent. You can configure up to 9 different users access to **Gateway Security** diagnostic and configuration screens. Allows for data manipulation during protocol **Translation Table** translation. Scaling and other data format changes can occur in the gateway. NOT EXACTLY WHAT YOU WERE LOOKING FOR? Protocol specific status, counters, and error Real Time Automation offers a full line of gateway products. messages are accessible within the gateway's Status and Counters Give us a call at 1-800-249-1612. Or, check out a listing at diagnostics page. They can also be delivered to a www.rtautomation.com/products. We also offer connected device. customizations for unique applications. Allows users to see and log start up sequences, **Diagnostic Logging Page** protocol specific messages & error messages.







ENGINERD SUPPORT



5-YEAR WARRANTY

İŞƏİİ Employee owned

Real Time Automation, Inc.

solutions@rtautomation.com