



REAL TIME AUTOMATION GATEWAY MODBUS RTU SERVER TO SNMP

460MMSM-N2E

KEY FEATURES

- ► Fully configurable Modbus **RTU Client**
- ► Connects up to 32 Modbus **RTU Servers**
- ► Get data directly from SNMP enabled devices
- ► Support for SNMPv1 & SNMPv2c
- ► Effortless browser-based configuration, no programming software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- 5-year hardware warranty

Connect your Modbus RTU Servers to SNMP enabled devices

The 460MMSM moves data between Modbus RTU Servers and SNMP Agents. With support for SNMPv1 and SNMPv2c it has never been easier to bring data from all your SNMP enabled network devices to your factory floor. Best of all, the product comes with 5-year warranty.

How Do I Use the 460MMSM-N2E in My Application?

Data from your SNMP Agent device is written directly regosters in Modbus RTU Servers. Receive SNMP trap information with up to 10 variable bindings. Use the RTA provided PC based tool to find and display all available Object Identifiers, then export to a file to be imported into the gateway and used for configuration.



Why Use RTA As Your Gateway Supplier?

Other companies might offer protocol gateways, but nobody matches the support and service you'll get from RTA. When you call, a real person picks up the phone. Sales gives you straight answers and solid recommendations. And when you need support, you'll talk to an engineer who helped build the product—no tickets, no waiting, just real help, right away.





MODBUS RTU CLIENT FEATURES	
Operation Mode	Modbus RTU Client
Function Codes Supported	1,2,3,4,5,6, 15 & 16
Swapping	Byte and Word Swapping
Maximum Modbus RTU Server Devices	32
Number Read/Write Scan Lines per RTU Server Device	200 Total - 100 reads & 100 writes
Scan Line Support	Up to 125 Registers or 512 Coils
SNMP MANAGER FEATURES	
Operation Mode	SNMPv1 Manager, SNMPv2c Manager
Maximum Agents Supported	32
Maximum Read/Write OIDs per Agent	100
Supported Set Data Types	Gauge32, Integer, Octet String
Supported Get Data Types	Counter32, Gauge32, Integer, Octet String, TimeTicks
SNMP Traps	Supported with up to 10 variable bindings with a 64 deep queue

	INCLUDED WITH GATEWAY	
, ,		5-year hardware warranty
		Unlimited firmware feature upgrades for life
	CAT5 crossover cable for direct connection to PC during programming	Complete, unlimited access to our industry leading support staff
	IPSetup software – automatically locates RTA gateway on the network	Unlimited firmware feature upgrades for life


ELECTRICAL / ENVIRONMENTAL

DC Input Voltage

Maximum Baud Rate	115K baud
Operating Temperature	-40 C to 85 C
Certification	RoHS-Compliant, UL, CUL, CE Approvals, Class I Div 2
ENCLOSURE / HARDWARE	
Size	5.40" x 3.83" x 1.19"
Weight	7.6 oz
Enclosure Type	Anodized Aluminum
Mounting	Din rail or panel mount
LEDs	Power LED & 2 general purpose LEDs on side

12-24 VDC

LEDs	Power LED & 2 general purpose LEDs on side	
GATEWAY FEATURES & FUNCTIONS		
Alarming	Set <, <=, >, >=, ==, !=, and change-of-state rules on any data moving through the gateway. If alarm rule is triggered an email notification can be sent.	
Gateway Security	You can configure up to 9 different users access to diagnostic and configuration screens.	
Translation Table	Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.	
Status and Counters	Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.	
Diagnostic Logging Page	Allows users to see and log start up sequences, protocol specific messages & error messages.	



NOT EXACTLY WHAT YOU WERE LOOKING FOR?

 $\ensuremath{\mathsf{RTA}}$ offers a full line of gateway products. Give us a call at 1-800-249-1612 or visit <u>www.rtautomation.com/products</u>. We also offer customizations for unique applications.

CATALOG# DESCRIPTION

460MMSM-N2E Connect up to 32 Modbus RTU Servers to up to 32 SNMP Agents















