460AAWS-NNA1

Serial ASCII to AWS (Amazon Web Services)

FEATURES

- Parse ASCII/HEX data in up to 50 segments by delimiter or offset
- Concatenate up to 50 data segments into a string
- AWS Certified Product
- Allows factory floor based devices to move its data to IT
- Effortless Browser
 Based Configuration,
 no programming
 software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- 5-Year Hardware Warranty

Connect Serial ASCII Devices to AWS IoT Core

The 460AAWS connects serial ASCII devices with a single connection to AWS. Allowing you to easily log data and leverage in populating dashboards. Best of all, the product is made in the USA and comes with 5-year warranty.

How Do I Use the 460AAWS-NNA1 in My Application?

Data elements inside ASCII strings are parsed and presented as topics to the AWS cloud platform. Conversely topics in your AWS cloud can be subscribed to and the values can be concatenated into an ASCII string.

If your ASCII device uses delimiters, the gateway can be configured to automatically remove the delimiters on incoming messages and add delimiters back in on outgoing messages.

Why Use Real Time Automation as a Gateway Supplier?

While there are certainly other companies offering protocol gateways, there is no one who provides the level of support and service that you receive from RTA.

When you call, a live person answers the phone. When you talk with sales, you will get honest answers and recommendations. When you get support, it is from an engineer who had a hand in the product's development, and support doesn't require a ticket or 24-hour wait.



A Solution, A Philosophy, the RTA Way. We understand the long hours spent on a factory floor and the pressure to keep a line running and product flowing. That's how Real Time Automation came to be. You want easy-to-use solutions where the hardest part is to open the box. You need customer support second to none. If you get all that and a fun customer experience all the better. Thirty years later, our mission remains the same: To move your data where you need it, when you need it, and how you need it.

Specification

ASCII FEATURES			
Operation Mode	Bidirectional ASCII Transmit and Receive		
Maximum Number of Devices Supported	1		
Concatenation	Concatenate up to 50 segments data in a delimeted ASCII sting		
Maximum Number of ASCII Characters Transferred	1024 in each direction		
Delimiter Processing	Incoming delimiters can be automatically removed; Outgoing delimiters automatically added if configured		
Parsing	Parse string of ASCII data in up to 50 segments by delimiter or offset		
MQTT CLIENT FEATURES			
Operation Mode	Amazon Web Services (AWS)		
Max Broker Connections	1 AWS		
Max Data Points Per Connection	250 Read Topics, 250 Write Topics		
Security	SSL certificate based cloud access		
Supported Data Formats	JSON		
Data Payload	Topic Name and Value		
INCLUDED WITH GATEWAY			
3' power cable with flying leads	5-year hardware warranty		
IPSetup software – automatically locates RTA gateway on the network	Unlimited firmware feature upgrades for life		
CAT5 crossover cable for direct connection to PC during programming	Complete, unlimited access to our industry leading support staff		
Manual			

ELECTRICAL / ENVIRONMENTA	L	
DC Input Voltage	12-24 VDC	
Maximum Baud Rate	115K baud	DIN Rail Mount
Operating Temperature	-40 C to 85 C	3.88
Certification	RoHS-Compliant, UL, CUL, CE Approvals	. '
ENCLOSURE / HARDWARE		
Size	3.88" x 2.57" x 1.06"	
Weight	5.5 oz	
Enclosure Type	Anodized Aluminum	2.57
Mounting	Din rail or panel mount	
LEDs	Power LED & 2 general purpose LEDs on side	Note: All dimensions
GATEWAY FEATURES & FUNCTIONS		are in Inches
Alarming	Set <, <=, >, >=, ==, !=, and change-of-state rules on any data moving through the gateway. If alarm rule is triggered an email notification can be sent.	60000 00
Gateway Security	You can configure up to 9 different users access to diagnostic and configuration screens.	1.06
Translation Table	Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.	
Status and Counters	Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.	NOT EXACTLY WHAT YOU WERE LOOKING FOR? Real Time Automation offers a full line of gateway products. Give us a call at 1-800-249-1612. Or, check out a listing at www.rtautomation.com/products . We also offer customizations for unique applications.
Diagnostic Logging Page	Allows users to see and log start up sequences, protocol specific messages & error messages.	

CATALOG #	DESCRIPTION
460AAWS-NNA1	Interface serial ASCII devices with Amazon Web Services (AWS) IoT Core













MADE IN THE USA

EXPERT SUPPORT

5-YEAR WARRANTY EMPLOYEE OWNED