

CONTACT US! 1-800-249-1612 rtautomation.com

Real Time Automation Gateways

460BCAWS-NNA1

BACnet/IP Servers to Amazon Web Services (AWS)

FEATURES

- Fully configurable BACnet/IP client
- BACnet/IP supports device, binary I/O/V, analog I/O/V, multistate I/O/V, and character string value object types
- AWS Certified Product
- Allows factory floor based devices to move its data to IT
- Effortless Browser Based Configuration, no programming software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- 5-Year Hardware Warranty

Connect BACnet/IP Server Devices to AWS IoT Core

The 460BCAWS moves data between up to 32 BACnet/IP devices and AWS. Connect your BACnet/IP devices to the AWS platform. Allowing you to easily log data and leverage in populating dashboards. The 460BCAWS delivers BACnet analog and binary data to AWS topics in a JSON format.

Best of all, the product comes with 5-year warranty.

How Do I Use the 460BCAWS-NNA1 in My Application?

Analog and binary BACnet data values become topics published or subscribed to within AWS.

SSL transport layer security protects the data moving from your operations network to the cloud.

Why Use Real Time Automation as a Gateway Supplier?

While there are certainly other companies offering protocol gateways, there is no one who provides the level of support and service that you receive from RTA.

When you call, a live person answers the phone. When you talk with sales, you will get honest answers and recommendations. When you get support, it is from an engineer who had a hand in the product's development, and support doesn't require a ticket or 24-hour wait.




A Solution, A Philosophy, the RTA Way. We understand the long hours spent on a factory floor and the pressure to keep a line running and product flowing. That's how Real Time Automation came to be. You want easy-to-use solutions where the hardest part is to open the box. You need customer support second to none. If you get all that and a fun customer experience all the better. Thirty years later, our mission remains the same: To move your data where you need it, when you need it, and how you need it.

Specification

BACNET IP CLIENT FEATURES	
Operation Mode	BACnet/IP Client
Supported Object Types	Device, BI/BO/BV, AI/AO/AV, MI/MO/MV, Character String Value
Supported Service Codes	Read Property-A, Read Property Multiple-A, Write Property-A, Write Property Multiple-A, Device Dynamic Binding-A
Maximum Connections	32
Number Read/Write Scan Lines per Device	200 Total - 100 reads & 100 writes
Scan Line Support	Up to 128 Objects
MQTT CLIENT FEATURES	
Operation Mode	Amazon Web Services (AWS)
Max Broker Connections	1 AWS
Max Data Points Per Connection	250 Read Topics, 250 Write Topics
Security	SSL certificate based cloud access
Supported Data Formats	JSON
Data Payload	Topic Name and Value
INCLUDED WITH GATEWAY	
3' power cable with flying leads	5-year hardware warranty
IPSetup software – automatically locates RTA gateway on the network	Unlimited firmware feature upgrades for life
CAT5 crossover cable for direct connection to PC during programming	Complete, unlimited access to our industry leading support staff
Manual	

ELECTRICAL / ENVIRONMENTAL DC Input Voltage 12-24 VDC Maximum Baud Rate 115K baud -40 C to 85 C **Operating Temperature** 3.88 Certification RoHS-Compliant, UL, CUL, CE Approvals **ENCLOSURE / HARDWARE** 3.88" x 2.57" x 1.06" Size Weight 5.5 oz Enclosure Type Anodized Aluminum 2.57 Din rail or panel mount Mounting LEDs Power LED & 2 general purpose LEDs on side Note: All dimensions are in Inches **GATEWAY FEATURES & FUNCTIONS** Set <, <=, >, >=, ==, !=, and change-of-state rules on any data moving through the gateway. If alarm rule 00000 Alarming is triggered an email notification can be sent. You can configure up to 9 different users access to **Gateway Security** diagnostic and configuration screens. 1.06 000 Allows for data manipulation during protocol Translation Table translation. Scaling and other data format changes can occur in the gateway. NOT EXACTLY WHAT YOU WERE LOOKING FOR? Protocol specific status, counters, and error Real Time Automation offers a full line of gateway products. messages are accessible within the gateway's Status and Counters Give us a call at 1-800-249-1612. Or, check out a listing at diagnostics page. They can also be delivered to a www.rtautomation.com/products. We also offer connected device. customizations for unique applications. Allows users to see and log start up sequences, **Diagnostic Logging Page** protocol specific messages & error messages.



Real Time Automation, Inc.

solutions@rtautomation.com