## 460BCAWS-NNA4

## **BACnet/IP Servers to Amazon Web Services (AWS)**

### **FEATURES**

- Fully configurable BACnet/IP client
- BACnet/IP supports device, binary I/O/V, analog I/O/V, multistate I/O/V, and character string value object types
- AWS Certified Product
- Allows factory floor based devices to move its data to IT
- Effortless Browser
   Based Configuration,
   no programming
   software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- 5-Year Hardware Warranty

#### **Connect BACnet/IP Server Devices to AWS IoT Core**

The 460BCAWS moves data between up to 32 BACnet/IP devices and AWS. Connect your BACnet/IP devices to the AWS platform. Allowing you to easily log data and leverage in populating dashboards. The 460BCAWS delivers BACnet analog and binary data to AWS topics in a JSON format. Best of all, the product comes with 5-year warranty.

#### How Do I Use the 460BCAWS-NNA4 in My Application?

Analog and binary BACnet data values become topics published or subscribed to within AWS.

SSL transport layer security protects the data moving from your operations network to the cloud.

#### Why Use Real Time Automation as a Gateway Supplier?

While there are certainly other companies offering protocol gateways, there is no one who provides the level of support and service that you receive from RTA.

When you call, a live person answers the phone. When you talk with sales, you will get honest answers and recommendations. When you get support, it is from an engineer who had a hand in the product's development, and support doesn't require a ticket or 24-hour wait.



A Solution, A Philosophy, the RTA Way. We understand the long hours spent on a factory floor and the pressure to keep a line running and product flowing. That's how Real Time Automation came to be. You want easy-to-use solutions where the hardest part is to open the box. You need customer support second to none. If you get all that and a fun customer experience all the better. Thirty years later, our mission remains the same: To move your data where you need it, when you need it, and how you need it.

# **Specification**

BACNET IP CLIENT FEATURES		
Operation Mode	BACnet/IP Client	
Supported Object Types	Device, BI/BO/BV, AI/AO/AV, MI/MO/MV, Character String Value	
Supported Service Codes	Read Property-A, Read Property Multiple-A, Write Property-A, Write Property Multiple-A, Device Dynamic Binding-A	
Maximum Connections	32	
Number Read/Write Scan Lines per Device	200 Total - 100 reads & 100 writes	
Scan Line Support	Up to 128 Objects	
MQTT CLIENT FEATURES		
Operation Mode	Amazon Web Services (AWS)	
Max Broker Connections	1 AWS	
Max Data Points Per Connection	250 Read Topics, 250 Write Topics	
Security	SSL certificate based cloud access	
Supported Data Formats	JSON	
Data Payload	Topic Name and Value	
INCLUDED WITH GATEWAY		
3' power cable with flying leads	5-year hardware warranty	
IPSetup software – automatically locates RTA gateway on the network	Unlimited firmware feature upgrades for life	
CAT5 crossover cable for direct connection to PC during programming	Complete, unlimited access to our industry leading support staff	
Manual		

ELECTRICAL / ENVIRONMENTA	<b>\L</b>	
DC Input Voltage	12-24 VDC	
Maximum Baud Rate	115K baud	DIN Rail Mount
Operating Temperature	-40 C to 85 C	
Certification	RoHS-Compliant, UL, CUL, CE Approvals	,
ENCLOSURE / HARDWARE		
Size	3.88" x 2.57" x 1.06"	
Weight	5.5 oz	
Enclosure Type	Anodized Aluminum	2.57
Mounting	Din rail or panel mount	
LEDs	Power LED & 2 general purpose LEDs on side	Note: All dimensions
GATEWAY FEATURES & FUNCTIONS		are in Inches
	Set <, <=, >, >=, ==, !=, and change-of-state rules on	,
Alarming	any data moving through the gateway. If alarm rule	0000
_	is triggered an email notification can be sent.	
Gateway Security	You can configure up to 9 different users access to	
	diagnostic and configuration screens.	1.06
	Allows for data manipulation during protocol	
Translation Table	translation. Scaling and other data format changes	
	can occur in the gateway.	
		NOT EXACTLY WHAT YOU WERE LOOKING FOR?
	Protocol specific status, counters, and error	Real Time Automation offers a full line of gateway products.
Status and Counters	messages are accessible within the gateway's	Give us a call at 1-800-249-1612. Or, check out a listing at
	diagnostics page. They can also be delivered to a	www.rtautomation.com/products. We also offer
	connected device.	customizations for unique applications.
Diagnostic Logging Page	Allows users to see and log start up sequences,	
Diagnostic Logging Fage	protocol specific messages & error messages.	

CATALOG #	DESCRIPTION
460BCAWS-NNA4	Connect up to 32 BACnet/IP server devices to Amazon Web Services (AWS) IoT Core









