

460ESAWS-NNA4

EtherNet/IP Scanner to Amazon Web Services (AWS)

FEATURES

- Fully configurable
 EtherNet/IP adapter
- Up to 480 bytes in each direction per adapter connection
- AWS Certified Product
- Allows factory floor based devices to move its data to IT
- Effortless Browser
 Based Configuration,
 no programming
 software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- 5-Year Hardware Warranty

Connect an EtherNet/IP PLC to AWS IoT Core

The 460ESAWS moves data between an EtherNet/IP scanner and the AWS platform. Allowing you to easily log data and leverage in populating dashboards. Best of all, the product is made in the USA and comes with 5-year warranty.

How Do I Use the 460ESAWS-NNA4 in My Application?

Map EtherNet/IP implicit IO data to topics in your AWS platform. SSL transport layer security protects the data moving from your operations network to the cloud.

Why Use Real Time Automation as a Gateway Supplier?

While there are certainly other companies offering protocol gateways, there is no one who provides the level of support and service that you receive from RTA.

When you call, a live person answers the phone. When you talk with sales, you will get honest answers and recommendations. When you get support, it is from an engineer who had a hand in the product's development, and support doesn't require a ticket or 24-hour wait.



A Solution, A Philosophy, the RTA Way. We understand the long hours spent on a factory floor and the pressure to keep a line running and product flowing. That's how Real Time Automation came to be. You want easy-to-use solutions where the hardest part is to open the box. You need customer support second to none. If you get all that and a fun customer experience all the better. Thirty years later, our mission remains the same: To move your data where you need it, when you need it, and how you need it.

Specification

ETHERNET/IP ADAPTER FEATURES			
Operation Mode	Class 1 I/O Adapter		
Message Support	Implicit Class 1 Cyclic I/O, Explicit Class 3 and UCMM Supported		
Data Types	BIT8,16 & 32; INT8, 16, 32 & 64; UINT8,16, 32 & 64; Float & Double		
Maximum EtherNet/IP Scanner Devices	Up to 10 can listen, only 8 can write I/O		
Maximum Data Supported	Up to 480 bytes in each direction per adapter connection		
Maximum IO Scan Rate	20 msec		
MQTT CLIENT FEATURES			
Operation Mode	Amazon Web Services (AWS)		
Max Broker Connections	1 AWS		
Max Data Points Per Connection	250 Read Topics, 250 Write Topics		
Security	SSL certificate based cloud access		
Supported Data Formats	JSON		
Data Payload	Topic Name and Value		
INCLUDED WITH GATEWAY			
3' power cable with flying leads	5-year hardware warranty		
IPSetup software – automatically locates RTA gateway on the network	Unlimited firmware feature upgrades for life		
CAT5 crossover cable for direct connection to PC during programming	Complete, unlimited access to our industry leading support staff		
Manual			

ELECTRICAL / ENVIRONMENTAL		
DC Input Voltage	12-24 VDC	
Maximum Baud Rate	115K baud	DIN Rail Mount
Operating Temperature	-40 C to 85 C	
Certification	RoHS-Compliant, UL, CUL, CE Approvals	
ENCLOSURE / HARDWARE		
Size	3.88" x 2.57" x 1.06"	
Weight	5.5 oz	
Enclosure Type	Anodized Aluminum	2.57
Mounting	Din rail or panel mount	
LEDs	Power LED & 2 general purpose LEDs on side	Note: All dimensions
GATEWAY FEATURES & FUNCTIONS		are in Inches
Alarming	Set <, <=, >, >=, ==, !=, and change-of-state rules on any data moving through the gateway. If alarm rule is triggered an email notification can be sent.	60000 00
Gateway Security	You can configure up to 9 different users access to diagnostic and configuration screens.	1.06
Translation Table	Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.	
Status and Counters	Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.	NOT EXACTLY WHAT YOU WERE LOOKING FOR? Real Time Automation offers a full line of gateway products. Give us a call at 1-800-249-1612. Or, check out a listing at www.rtautomation.com/products . We also offer customizations for unique applications.
Diagnostic Logging Page	Allows users to see and log start up sequences, protocol specific messages & error messages.	

CATALOG #	DESCRIPTION
460ESAWS-NNA4	Easily and securely connect EtherNet/IP PLCs to Amazon Web Services (AWS) IoT Core













MADE IN THE USA

EXPERT SUPPORT

5-YEAR WARRANTY EMPLOYEE OWNED