## 460MMAWS-N2E

## **Modbus RTU Server to Amazon Web Services (AWS)**

## **FEATURES**

- Fully configurable Modbus RTU Client
- Connects up to 32
   Modbus RTU Servers
- AWS Certified Product
- Allows factory floor based devices to move its data to IT
- Effortless Browser
   Based Configuration,
   no programming
   software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- 5-Year Hardware Warranty

# **Bridge up to 31 Modbus RTU Server Devices to AWS IoT Core**

The 460MMAWS moves data between up to 32 Modbus RTU Server devices and AWS. Allowing you to easily log data and leverage in populating dashboards. Best of all, the product is made in the USA and comes with 5-year warranty.

#### How Do I Use the 460MMAWS-N2E in My Application?

Modbus register and coil data is mapped to and from topics in AWS. SSL transport layer security protects the data moving from your operations network to the cloud.

### Why Use Real Time Automation as a Gateway Supplier?

While there are certainly other companies offering protocol gateways, there is no one who provides the level of support and service that you receive from RTA.

When you call, a live person answers the phone. When you talk with sales, you will get honest answers and recommendations. When you get support, it is from an engineer who had a hand in the product's development, and support doesn't require a ticket or 24-hour wait.



A Solution, A Philosophy, the RTA Way. We understand the long hours spent on a factory floor and the pressure to keep a line running and product flowing. That's how Real Time Automation came to be. You want easy-to-use solutions where the hardest part is to open the box. You need customer support second to none. If you get all that and a fun customer experience all the better. Thirty years later, our mission remains the same: To move your data where you need it, when you need it, and how you need it.

## **Specification**

MODBUS RTU CLIENT FEATURES	
Operation Mode	Modbus RTU Client
Function Codes Supported	1,2,3,4,5,6, 15 & 16
Swapping	Byte and Word Swapping
Maximum Modbus RTU Server Devices	32
Number Read/Write Scan Lines per RTU Server Device	200 Total - 100 reads & 100 writes
Scan Line Support	Up to 125 Registers or 512 Coils
MQTT CLIENT FEATURES	
Operation Mode	Amazon Web Services (AWS)
Max Broker Connections	1 AWS
Max Data Points Per Connection	250 Read Topics, 250 Write Topics
Security	SSL certificate based cloud access
Supported Data Formats	JSON
Data Payload	Topic Name and Value
INCLUDED WITH GATEWAY	
3' power cable with flying leads	5-year hardware warranty
IPSetup software – automatically locates RTA gateway on the network	Unlimited firmware feature upgrades for life
CAT5 crossover cable for direct connection to PC during programming	Complete, unlimited access to our industry leading support staff
Manual	

ELECTRICAL / ENVIRONMENTAL				
DC Input Voltage	12-24 VDC			
Maximum Baud Rate	115K baud	□ (o þ¤)		
Operating Temperature	-40 C to 85 C	<b>≒</b>		
Certification	RoHS-Compliant, UL, CUL, CE Approvals, Class I Div 2	3.83		
ENCLOSURE / HARDWARE		0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0		
Size	5.40" x 3.83" x 1.19"			
Weight	7.6 oz			
Enclosure Type	Anodized Aluminum			
Mounting	Din rail or panel mount			
LEDs	Power LED & 2 general purpose LEDs on side			
GATEWAY FEATURES & FUNCTIONS				
Alarming	Set <, <=, >, >=, ==, !=, and change-of-state rules on any data moving through the gateway. If alarm rule is triggered an email notification can be sent.			
Gateway Security	You can configure up to 9 different users access to diagnostic and configuration screens.			
Translation Table	Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.			
Status and Counters	Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.	NOT EXACTLY WHAT YOU WERE LOOKING FOR?  Real Time Automation offers a full line of gateway products.  Give us a call at 1-800-249-1612. Or, check out a listing at  www.rtautomation.com/products. We also offer  customizations for unique applications.		
Diagnostic Logging Page	Allows users to see and log start up sequences, protocol specific messages & error messages.			

CATALOG #	DESCRIPTION
460MMAWS-N2E	Easily and securely connect Modbus RTU devices to Amazon Web Services (AWS) IoT Core













MADE IN THE USA

EXPERT SUPPORT

5-YEAR WARRANTY

**EMPLOYEE OWNED**