### 460MSBM-NNA4

## **BACnet MS/TP to Modbus TCP/IP Client**

## **FEATURES**

- Fully configurable Modbus TCP/IP server
- Move up to 100 groups of 512 contiguous coils or 512 contiguous registers to or from your Modbus TCP/IP client
- Fully configurable BACnet MS/TP Manager
- BACnet MS/TP supports device, binary I/O/V, analog I/O/V, multi-state I/O/V, and character string value object types
- Effortless Browser
   Based Configuration,
   no programming
   software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- 5-Year Hardware Warranty

#### Connect BACnet MS/TP Devices to a Modbus TCP/IP Client

The 460MSBM moves data between a network of up to 32 BACnet MS/TP devices and a Modbus TCP/IP client.

It's a perfect tool to get your Modbus TCP/IP data tied in with your BACnet MS/TP devices.

#### How Do I Use the 460MSBM-NNA4 in My Application?

Modbus register data is mapped to BACnet analog objects and Modbus coil data is mapped to binary objects on BACnet. The final step to add meaning names to each BACnet object for easy discovery in the BMS. It really is that simple.

#### Why Use Real Time Automation as a Gateway Supplier?

While there are certainly other companies offering protocol gateways, there is no one who provides the level of support and service that you receive from RTA.

When you call, a live person answers the phone. When you talk with sales, you will get honest answers and recommendations. When you get support, it is from an engineer who had a hand in the product's development, and support doesn't require a ticket or 24-hour wait.



A Solution, A Philosophy, the RTA Way. We understand the long hours spent on a factory floor and the pressure to keep a line running and product flowing. That's how Real Time Automation came to be. You want easy-to-use solutions where the hardest part is to open the box. You need customer support second to none. If you get all that and a fun customer experience all the better. Thirty years later, our mission remains the same: To move your data where you need it, when you need it, and how you need it.

# **Specification**

MODBUS TCP SERVER FEATURES		
Operation Mode	Modbus TCP/IP Server	
Function Codes Supported	1,2,3,4,5,6, 15 & 16	
Swapping	Byte and Word Swapping	
Maximum Modbus TCP/IP Client Connections	10	
Contiguous Data Areas	200 Total - 100 reads & 100 writes	
Data Area Limits	512 Contiguous Coils or 512 Contiguous Registers	
BACNET MS/TP MANAGER FEATURES		
Operation Mode	BACnet MS/TP Manager Initiator	
Supported Object Types	Device, BI/BO/BV, AI/AO/AV, MI/MO/MV, Character String Value	
Supported Service Codes	Read Property-A, Read Property Multiple-A, Write Property-A, Write Property Multiple-A, Device Dynamic Binding-A	
Maximum Connections	32	
Number Read/Write Scan Lines per Device	200 Total - 100 reads & 100 writes	
Scan Line Support	Up to 128 Objects	
INCLUDED WITH GATEWAY		
3' power cable with flying leads	5-year hardware warranty	
IPSetup software – automatically locates RTA gateway on the network	Unlimited firmware feature upgrades for life	
CAT5 crossover cable for direct connection to PC during programming	Complete, unlimited access to our industry leading support staff	
Manual		

ELECTRICAL / ENVIRONMENTA	<b>\</b> L	
DC Input Voltage	12-24 VDC	
Maximum Baud Rate	115K baud	DIN Rail Mount
Operating Temperature	-40 C to 85 C	
Certification	RoHS-Compliant, UL, CUL, CE Approvals	,
ENCLOSURE / HARDWARE		
Size	3.88" x 2.57" x 1.06"	
Weight	5.5 oz	
Enclosure Type	Anodized Aluminum	2.57
Mounting	Din rail or panel mount	
LEDs	Power LED & 2 general purpose LEDs on side	Note: All dimensions
GATEWAY FEATURES & FUNCTIONS		are in Inches
	Set <, <=, >, >=, ==, !=, and change-of-state rules on	·
Alarming	any data moving through the gateway. If alarm rule	0000
<u> </u>	is triggered an email notification can be sent.	
Gateway Security	You can configure up to 9 different users access to	
	diagnostic and configuration screens.	
	Allows for data manipulation during protocol	
Translation Table	translation. Scaling and other data format changes	
	can occur in the gateway.	
	Protocol specific status, counters, and error	NOT EXACTLY WHAT YOU WERE LOOKING FOR?
	messages are accessible within the gateway's	Real Time Automation offers a full line of gateway products.
Status and Counters	diagnostics page. They can also be delivered to a	Give us a call at 1-800-249-1612. Or, check out a listing at
	connected device.	www.rtautomation.com/products. We also offer
	connected device.	customizations for unique applications.
Diagnostic Logging Page	Allows users to see and log start up sequences,	
2.20.19946 2088118 1 486	protocol specific messages & error messages.	

CATALOG #	DESCRIPTION
460MSBM-NNA4	Connects a Modbus TCP client with as many as 32 BACnet MS/TP Subordinates









