460MSMM-N700

Modbus RTU to Modbus TCP/IP

FEATURES

- Fully configurable Modbus TCP/IP server
- Move up to 100 groups of 512 contiguous coils or 512 contiguous registers to or from your Modbus TCP/IP client
- Fully configurable Modbus RTU Client
- Connects up to 32
 Modbus RTU Servers
- Effortless Browser
 Based Configuration,
 no programming
 software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- 5-Year Hardware Warranty

Get Your Modbus RTU Server Devices Connected to Your Modbus TCP/IP Client

The 460MSMM moves data between up to 32 Modbus RTU Server devices and a Modbus TCP/IP client devices.

Best of all, the product comes with 5-year warranty.

How Do I Use the 460MSMM-N700 in My Application?

Connect Modbus RTU Servers to Modbus TCP/IP controller. In the gateway, you configure what data it will read and write from the Modbus TCP/IP client and each Server device connection.

It's really that simple. Need to modify your data as it passes from one protocol to the other? No problem. Each data mapping you apply can be modified with up to three mathematic functions. Add 4 to a value, multiply by 4 and divide by 10 with ease.

Why Use Real Time Automation as a Gateway Supplier?

While there are certainly other companies offering protocol gateways, there is no one who provides the level of support and service that you receive from RTA.

When you call, a live person answers the phone. When you talk with sales, you will get honest answers and recommendations. When you get support, it is from an engineer who had a hand in the product's development, and support doesn't require a ticket or 24-hour wait.



A Solution, A Philosophy, the RTA Way. We understand the long hours spent on a factory floor and the pressure to keep a line running and product flowing. That's how Real Time Automation came to be. You want easy-to-use solutions where the hardest part is to open the box. You need customer support second to none. If you get all that and a fun customer experience all the better. Thirty years later, our mission remains the same: To move your data where you need it, when you need it, and how you need it.

Specification

MODBUS TCP SERVER FEATURES	
Operation Mode	Modbus TCP/IP Server
Function Codes Supported	1,2,3,4,5,6, 15 & 16
Swapping	Byte and Word Swapping
Maximum Modbus TCP/IP Client Connections	10
Contiguous Data Areas	200 Total - 100 reads & 100 writes
Data Area Limits	512 Contiguous Coils or 512 Contiguous Registers
MODBUS RTU CLIENT FEATURES	
Operation Mode	Modbus RTU Client
Function Codes Supported	1,2,3,4,5,6, 15 & 16
Swapping	Byte and Word Swapping
Maximum Modbus RTU Server Devices	32
Number Read/Write Scan Lines per RTU Server Device	200 Total - 100 reads & 100 writes
Scan Line Support	Up to 125 Registers or 512 Coils
INCLUDED WITH GATEWAY	
3' power cable with flying leads	5-year hardware warranty
IPSetup software – automatically locates RTA gateway on the network	Unlimited firmware feature upgrades for life
CAT5 crossover cable for direct connection to PC during programming	Complete, unlimited access to our industry leading support staff
Manual	

ELECTRICAL / ENVIRONMENTAL		
DC Input Voltage	12-24 VDC	
Maximum Baud Rate	115K baud	
Operating Temperature	-40 C to 85 C	
Certification	RoHS-Compliant, UL, CUL, CE Approvals	Internet S
ENCLOSURE / HARDWARE		104/14
Size	4.19" x 3.25" x 1"	3,25
Weight	6.5 oz	
Enclosure Type	Anodized Aluminum	Note: All dimension are n inches
Mounting	Din rail or panel mount	are n inches
LEDs	Power LED, Ethernet link/data LED, & Ethernet speed LED	-1.00
GATEWAY FEATURES & FUNCT	IONS	Din Rail
	Set <, <=, >, >=, ==, !=, and change-of-state rules on	Uin Rail
Alarming	any data moving through the gateway. If alarm rule	
	is triggered an email notification can be sent.	Panel Mount
Gateway Security	You can configure up to 9 different users access to	ranei would
	diagnostic and configuration screens.	
Translation Table	Allows for data manipulation during protocol	
	translation. Scaling and other data format changes	
	can occur in the gateway.	
	Protocol specific status, counters, and error	NOT EXACTLY WHAT YOU WERE LOOKING FOR?
Status and Counters	messages are accessible within the gateway's	Real Time Automation offers a full line of gateway products
	diagnostics page. They can also be delivered to a	Give us a call at 1-800-249-1612. Or, check out a listing at
	connected device.	www.rtautomation.com/products. We also offer
	connected device.	customizations for unique applications.
Diagnostic Logging Page	Allows users to see and log start up sequences,	
00.191.191	protocol specific messages & error messages.	

CATALOG #	DESCRIPTION
460MSMM-N700	Connects a Modbus TCP client with as many as 32 Modbus RTU Servers









