

CONTACT US! 1-800-249-1612 rtautomation.com

Real Time Automation Gateways

460SCAWS-NNA4

Siemens PLC to Amazon Web Services (AWS)

FEATURES

- Supports connections to five Siemens S7 PLCs
- Up to 150 read and 150 write requests per connection
- AWS Certified Product
- Allows factory floor based devices to move its data to IT
- Effortless Browser Based Configuration, no programming software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- 5-Year Hardware Warranty

Bridge Siemens Controllers to AWS IoT Core

The 460SCAWS moves data between a Siemens controller and the AWS platform. Allowing you to easily log data and leverage in populating dashboards. Best of all, the product comes with 5-year warranty.

How Do I Use the 460SCAWS-NNA4 in My Application?

You can map inputs and outputs as a block on memory in the data table of the Siemens PLC to topics published or subscribed to in AWS. SSL transport layer security protects the data moving from your operations network to the cloud.

Why Use Real Time Automation as a Gateway Supplier?

While there are certainly other companies offering protocol gateways, there is no one who provides the level of support and service that you receive from RTA.

When you call, a live person answers the phone. When you talk with sales, you will get honest answers and recommendations. When you get support, it is from an engineer who had a hand in the product's development, and support doesn't require a ticket or 24-hour wait.




A Solution, A Philosophy, the RTA Way. We understand the long hours spent on a factory floor and the pressure to keep a line running and product flowing. That's how Real Time Automation came to be. You want easy-to-use solutions where the hardest part is to open the box. You need customer support second to none. If you get all that and a fun customer experience all the better. Thirty years later, our mission remains the same: To move your data where you need it, when you need it, and how you need it.

Specification

Siemens S7 CLIENT FEATURES	
PLC Support	S7 300/400/1200/1500
Maximum Number of PLCs Supported	5
Maximum Number of Inputs/Outputs per PLC	150
Maximum Number of Bytes per Scan Line	400
Memory Area Access	Input (I), Output (Q), and Data Block(DB)
Supported Data Types	8 Bit Int, 16 Bit Int, 32 Bit Int, 32 Bit Float, Bool and Char Array
MQTT CLIENT FEATURES	
Operation Mode	Amazon Web Services (AWS)
Max Broker Connections	1 AWS
Max Data Points Per Connection	250 Read Topics, 250 Write Topics
Security	SSL certificate based cloud access
Supported Data Formats	JSON
Data Payload	Topic Name and Value
INCLUDED WITH GATEWAY	
3' power cable with flying leads	5-year hardware warranty
IPSetup software – automatically locates RTA gateway on the network	Unlimited firmware feature upgrades for life
CAT5 crossover cable for direct connection to PC during programming	Complete, unlimited access to our industry leading support staff
Manual	

ELECTRICAL / ENVIRONMENTAL DC Input Voltage 12-24 VDC Maximum Baud Rate 115K baud -40 C to 85 C **Operating Temperature** 3.88 Certification RoHS-Compliant, UL, CUL, CE Approvals **ENCLOSURE / HARDWARE** 3.88" x 2.57" x 1.06" Size Weight 5.5 oz Enclosure Type Anodized Aluminum 2.57 Din rail or panel mount Mounting LEDs Power LED & 2 general purpose LEDs on side Note: All dimensions are in Inches **GATEWAY FEATURES & FUNCTIONS** Set <, <=, >, >=, ==, !=, and change-of-state rules on any data moving through the gateway. If alarm rule 00000 Alarming is triggered an email notification can be sent. You can configure up to 9 different users access to **Gateway Security** diagnostic and configuration screens. 1.06 000 Allows for data manipulation during protocol Translation Table translation. Scaling and other data format changes can occur in the gateway. NOT EXACTLY WHAT YOU WERE LOOKING FOR? Protocol specific status, counters, and error Real Time Automation offers a full line of gateway products. messages are accessible within the gateway's Status and Counters Give us a call at 1-800-249-1612. Or, check out a listing at diagnostics page. They can also be delivered to a www.rtautomation.com/products. We also offer connected device. customizations for unique applications. Allows users to see and log start up sequences, **Diagnostic Logging Page** protocol specific messages & error messages.







ENGINERD SUPPORT







solutions@rtautomation.com